

RISH MIT 30

Analog Digital Multimeter with Insulation Resistance Measurement

Product Features:

RISH MIT 30 is Analog Digital Multimeter with insulation resistance measurement, which measures VAC, VDC, VAC+DC, Frequency, mA DC, mA AC+DC, Resistance, continuity, Diode, Farad, AC current measurement with clip-on sensor and insulation resistance measurement.

Insulation resistance measurement up to 3GΩ.

Insulation resistance measurement up to 3GΩ with Test voltages selection: 50 V, 100V, 250V, 500V and 1000V.

Route mean square value with distorted wave form.

Measuring principal employed permits the measurement of root mean square value (TRMS) OF AC quantities and mixed quantities (AC and DC) regardless of wave form.

AC Current measurement with clip-on sensor

Current measurement up to 300A with clip-on sensor having ratio 1mv/10mA.

Min/Max Function

By pressing min/max button instrument will start recording minimum and maximum readings.

Temperature measurement

Temperatures from -200 to 800°C using pt100 and pt 1000 sensors.

AUTO POWER OFF

In order to save the power of the Batteries, the meter will automatically shut OFF if it detects no activity for 10 minutes.

Continuity test

This permits resting for short circuit and open circuit. In addition to the display, a facility of sound signal is available.

AUTO and MANUAL ranging modes.

In AUTO ranging mode the instrument automatically selects the range with best resolution depending on the applied input. In MANUAL ranging mode range is user selectable using **MAN** key.

Indication of negative values on the analog scale.

When measuring DC quantities, also negative values are shown on the analog scale so that variations of the measured value can be observed at the Zero point.

Protection from dust and water:

Instrument: IP50

For terminals: IP20 as per IEC60529

Applicable International Safety standards

1000 V CAT II/600V CAT III as per International Safety standard IEC 61010-1-2001 and IEC 61557.

Signaling in the case of a blown fuse.

The display shows "FUZE" in case of blown fuse.

Automatic blocking socket (ABS)

The automatic terminal blocking system prevents incorrect connection of test lead and incorrect selection of measurement quantity, which provide safety to the user.

RISH MIT 30



Interface and software RISH com 100.

The multimeters are fitted with a serial RS-232 C interface via which the measured values can be transmitted to a PC. These values, electrically isolated, are transmitted to the attachable interface adaptor with infrared light through the case.

Analog Scale

Analog scale that updates at the rate 20 times/sec to observe fluctuations in input.

CONTINUOUS ON MODE

In this mode, AUTO POWER OFF is disabled.

DATA Hold Function

By pressing DATA HOLD button, reading on the display can be latched for Hands free operation.

NULL ZERO Correction for Resistance

For Low ohm measurement, the lead resistance can be compensated by pressing the shift key (Yellow Key)

NULL ZERO Correction for Capacitance

Null zero connection for capacitance. For nF range, stray capacitance can be compensated by shift key (Yellow Key)

Diode Measurement

For testing diode and transistors, diode measurement function is available.

Display with Backlit.

For clear visibility in dark conditions, RISH MIT 30 is featured with backlit.



Rishabh Instruments

RISHABH
INSTRUMENTS
Measure, Control & Record with a Difference

RISHABH INSTRUMENTS PVT.LTD.

F-31, MIDC, Satpur, Nashik-422 007, India.

Tel.: +91 253 2202160, 2202202 Fax : +91 253 2351064

E-mail : India :- marketing@rishabh.co.in

International :- exp.marketing@rishabh.co.in

www.rishabh.co.in

Version: I 07/03/2010

RISH MT 30

Analog Digital Multimeter with Insulation Resistance Measurement

Reference conditions for Accuracy:

Reference temperature	23°C ± 2K
Relative Humidity	45%...55% RH
Waveform of measured quantity	Sinusoidal
Input frequency	50 or 60 Hz ±2%
Battery Voltage	8 V ± 0.1 V

Applicable Standards:

For Use as a Insulation Measuring Instrument.	IEC 61557: Devices for testing, measuring and monitoring protective safety measures in system with voltages of up to 1000 V A.C. and 1500 V D.C.
	IEC 61557- 1: For general requirements
	IEC 61557- 2: For Insulation resistance measuring instruments
EMC	IEC 61326: Class B
Immunity	IEC 61000-4-2 8 KV atmosphere discharge, 4 KV contact discharge
	IEC 61000-4-3 : 3 V/m

Safety

	IEC 61010-1-2001
IP for water & dust	IEC60529
Pollution degree:	2
Installation category:	III
High Voltage Test	3.5 kV (IEC 61010-1-2001)

Environmental

Operating temperature	-20 to +50°C
Storage temperature	-25 to +70°C
Relative humidity	<75% non condensing.
Terminal Protection	IP20 for terminals
Altitude	Up to 2000 m

Battery

Battery Voltage	6 x 1.5 V Cells
Battery type	Alkaline manganese Dioxide cell as per IEC LR 03 , ANSI 24A (Size AAA)
Battery Life	Minimum 600 hours on Vdc, Adc ,240 hours on Vac, Aac, For MΩISO @1000 V, 800 Measurements possible with nominal current MΩISO @500,250V, 100V, 50 V, 2400 Measurements possible with nominal current.

Interface

Type	RS232C, serial, as per DIN 19241.
Data transmission	Optically with infrared light through the case.
Baud rate	8192 bits/s.



RISHABH
INSTRUMENTS

Measure, Control & Record with a Difference

RISHABH INSTRUMENTS PVT.LTD.

F-31, MIDC, Satpur, Nashik-422 007, India.

Tel.: +91 253 2202160, 2202202 Fax : +91 253 2351064

E-mail : India :- marketing@rishabh.co.in

International :- exp.marketing@rishabh.co.in

www.rishabh.co.in

RISH MT 30

Analog Digital Multimeter with Insulation Resistance Measurement

Specifications:

Measuring function	Measuring range	Resolution	Input impedance	Intrinsic error of digital display ± (...% of rdg + ...digit) at reference conditio	Over load capacity ¹⁾					
					Over load value	Overload duration				
V dc	30.00 mV	10 µV	>10 GΩ // <40pF	0.5 + 3 ²⁾	1000 V DC AC eff / rms Sine wave	Continuously				
	300.0 mV	100 µV	>10 GΩ // <40pF	0.5 + 3						
	3.000 V	1 mV	11 MΩ // <40pF	0.25 + 1						
	30.00 V	10 mV	10 MΩ // <40pF	0.25 + 1						
	300.0 V	100 mV	10 MΩ // <40pF	0.25 + 1						
	1000 V	1 V	10 MΩ // <40pF	0.35 + 1						
V ~	3.000 V	1 mV	11 MΩ // <40pF	1.0 + 3 (>10 Digits)			1000 V DC AC eff / rms Sine wave	Continuously		
	30.00 V	10 mV	10 MΩ // <40pF							
	300.0 V	100 mV	10 MΩ // <40pF							
	1000 V	1V	10 MΩ // <40pF							
V AC+DC	3.000 V	1 mV	11 MΩ // <40pF	1.0 + 3 (>10 Digits)	1000 V DC AC eff / rms Sine wave	Continuously				
	30.00 V	10 mV	10 MΩ // <40pF							
	300.0 V	100 mV	10 MΩ // <40pF							
	1000 V	1V	10 MΩ // <40pF							
A AC with clamp 6)	30/300 A	10/100mA	–	0.5 +5					–	--
A DC	Voltage Drop								0.36 A	Continuously
	300.0 µA	100 nA	15 mV	0.5+5 (>10 Digit)						
	3.000 mA	1 µA	150 mV	0.5+2						
	30.00 mA	10 µA	650 mV	0.5+5 (>10 Digit)						
	300.0 mA	100 µA	1V	0.5+5						
A AC+DC	3.000 mA	1 µA	150 mV	1.5+4 (>10 Digit)	0.36 A	Continuously				
	300.0 mA	100 µA	1 V	1.5+4 (>10 Digit)						
Ω	No load voltage				1000 V DC AC eff / rms Sine wave	10 sec				
	30.00 Ω	10 mΩ	Max. 3.2 V	0.5 + 3 ²⁾						
	300.0 Ω	100 mΩ	Max. 3.2 V	0.5 + 3						
	3.000 KΩ	1Ω	Max. 1.25 V	0.4 + 1						
	30.00 KΩ	10 Ω	Max. 1.25 V	0.4 + 1						
	300.0 KΩ	100 Ω	Max. 1.25 V	0.4 + 1						
	3.000 MΩ	1 KΩ	Max. 1.25 V	0.6 + 1						
	30.00 MΩ	10 KΩ	Max. 1.25 V	2.0 + 1						
→	2.000 V	1 mV	Max. 3.2 V	0.25 + 1						

Measuring function	Measuring range	Resolution	Discharge resistance	U0 max.	Intrinsic error of digital display ± (...% of rdg + ...digit) at reference condition	Over load capacity ¹⁾	
						Over load value	Overload duration
Farad ⊞	30.00 nF	10 pF	250 KΩ	2.5 V	1.0 + 3 ²⁾	1000 V DC AC eff / rms Sine	10 sec
	300.0 nF	100 pF	250 KΩ	2.5 V	1.0 + 3		
	3.000 µF	1 nF	25 KΩ	2.5 V	1.0 + 3		
	30.00 µF	10 nF	25 KΩ	2.5 V	3.0 + 3		



RISHABH INSTRUMENTS
RISHABH
Measure, Control & Record with a Difference

RISHABH INSTRUMENTS PVT.LTD.
F-31, MIDC, Satpur, Nashik-422 007, India.
Tel.: +91 253 2202160, 2202202 Fax : +91 253 2351064
E-mail : India :- marketing@rishabh.co.in
International :- exp.marketing@rishabh.co.in
www.rishabh.co.in

RISH MT 30

Analog Digital Multimeter with Insulation Resistance Measurement

Measuring function	Measuring range		Resolution	Discharge resistance	U0 max.	Intrinsic error of digital display ± (...% of rdg + ...digit) at reference condition	Over load capacity ¹⁾	
							Over load value	Overload duration
Hz				f min V dc	f min V ~	0.5 + 1 ³⁾	≤ 3 kHz 1000 v ≤ 30 kHz; 300 V ≤100 kHz 30 V	Continuously
	300.0 Hz		0.1 Hz	1 Hz	45 Hz			
	3.000 KHz		1 Hz	1 Hz	45 Hz			
	30.00 KHz		10 Hz	10 Hz	45 Hz			
	100.0 KHz		100 Hz	100 Hz	100 Hz			
%	2.0...98.0%		0.1 %	2 Hz	--	2 Hz... 1kHz ± 5 Digit ⁴⁾ 1 kHz ... 10 kHz; ± 5 Digit / kHz ⁴⁾		
°C	Pt 100	-200.0... +200.0 °C	0.1 °C	-	--	2 Kelvin + 5 Digit ⁵⁾ 1.0 + 5 ⁵⁾	1000 V DC AC eff / rms Sine	10 sec
		+200.0... +850.0 °C	0.1 °C					
	Pt 1000	-100.0... +200.0 °C	0.1 °C	-	--	2 Kelvin + 2 Digit ⁵⁾ 1.0 + 2 ⁵⁾		
		+200.0... +850.0 °C	0.1 °C					

Influence Quantities and Variations:

Influence Quantity	Measuring Range	Resolution	Intrinsic error of digital display ± (...% of rdg + ...digit) at reference condition
V1MΩ ⁷⁾	0...1000 V AC+DC	1V	1+10 D
MQIT@1000V 8)	0...1000 V AC+DC	1V	1+10 D
MQIT Un=50 V	0.100...1.600 MΩ	1KΩ	--
	01.40...16.00 MΩ	10 KΩ	5 + 15 D
MQIT Un=100 V	014.0...155.0 MΩ	100 KΩ	--
	0.100...3.100 MΩ	1KΩ	--
	02.80...31.00 MΩ	10 KΩ	5 + 15 D
MQIT Un=250 V	028.0...310.0 MΩ	100 KΩ	--
	0.100...0.800 MΩ	1KΩ	--
	00.70...08.00 MΩ	10 KΩ	3 + 10 D
	007.0...080.0 MΩ	100 KΩ	--
MQIT Un=500 V	0070...0775 MΩ	1MΩ	--
	0.100...1.600 MΩ	1KΩ	--
	01.40...16.00 MΩ	10 KΩ	3 + 10 D
	014.0...160.0 MΩ	100 KΩ	--
MQIT Un=1000 V	0140...1600 MΩ	1MΩ	--
	0.100...3.100 MΩ	1KΩ	--
	02.80...31.00 MΩ	10 KΩ	3 + 10 D
	028.0...310.0 MΩ	100 KΩ	--
	0280...3100 MΩ	1MΩ	--

1) At 0° ... + 40 °C

2) With zero adjustment, without zero adjustment + 50 digits

3) Range

3 V ac/dc: Ue = 1.5 V eff/rms ... 100 V eff/rms

30 V ac/dc: Ue = 15 V eff/rms ... 300 V eff/rms

300 V ac/dc: Ue = 150 V eff/rms ... 1000 V eff/rms

4) On the range 3 V dc, square – wave signal positive on one side 5 ... 15 V,

f = const., not 163.84 Hz or integral multiple.

5) Without sensor.

6) Measurement with clip-on current sensor with ratio 1mv/10mA.

7) Discharge the DUT through 1MΩ resistance, before insulation resistance measurement. LCD displays value of voltage present on DUT.

8) In this switch position live circuit detection (VAD+DC) is done before insulation measurement. If voltage present is greater than 50V (AC+DC), insulation resistance measurement function is disabled and LCD displays value of voltage present on DUT.

Influence Quantity	Range of Influence	Measured Quantity / measuring Range	Variation ¹⁾ ± (...% of rdg. +digits)	
Temperature	0 °C +21 °C and +25 °C...+40°C MΩIT 0.25 + 2	30/300 mV dc	1.0 + 3	
		3...300 V dc	0.15 + 1	
		1000 V dc	0.2 + 1	
		V ~	0.4 + 1	
		300µA ... 300mA DC	0.5+1	
		AAC+DC	0.75+3	
		30 Ω 2)	0.15 + 2	
			300 Ω 0.25 + 2	
		3 KΩ – 3 MΩ	0.15 + 1	
		30 MΩ	1.0 + 1	
		30 nF ²⁾ – 3 µF	0.5 + 2	
		30 µF	2.0 + 2	
		Hz	0.5 + 1	
		%	± 5 digits	
Frequency of the measured quantity	15 Hz...< 30 Hz	3...1000 V ~	1.0 + 3	
	30 Hz...< 45 Hz		0.5 + 3	
	> 65 Hz... 400 Hz		2.0 + 3	
	Wave form of the measured quantity ³⁾	>400 Hz...1 KHz	3...300 V ~	3.0 + 3
		20Hz ...< 45 Hz	1000 V ~	3.0 + 7
		>66 Hz... 1 kHz	A~	2.0 + 3
Crest factor CF	1...3	V ~ 4), A~ 4)	3.0 + 3	
	3...5		± 1 % of rdg	
Battery Voltage	⎓ ⁵⁾ ...< 7.9 V > 8.1 V ...10.0 V	V DC	± 3 % of rdg	
		V~, ADC	2 Digit	
		AAC+DC	4 Digit	
		30Ω / 300 Ω/°C	6 Digit	
		3 kΩ – 30MΩ, MΩIT	4 Digit	
		nF, µF,	3 Digit	
		Hz	1 Digit	
%	1 Digit			
Relative humidity	75%	V~,V DC AAC+DC,A DC	3 Days	
	3 Days	Ω	1 x intrinsic error	
	Meter off	Hz °C		
DATA	-	%	± 1 digits	
MIN/MAX	-	V ac/dc , A ac/dc, clamp	± 2 digits	

- 1) With temperature: Error data apply per 10 K change in temperature.
With frequency: Error data apply to a display from 300 digits onwards.
- 2) With zero adjustment.
- 3) With unknown waveform (crest factor CF > 2), measure with manual range selection
- 4) With the exception of sinusoidal waveform.
- 5) After the "⎓" symbol is displayed.



RISH MT 30

Analog Digital Multimeter with Insulation Resistance Measurement

Influence Quantity	Range of Influence	measuring Range	Attenuation
Common Mode interference voltage	Noise quantity max. 1000 V	V dc 3V~, 300 V~ 30V~	> 120 dB > 70 dB
		1000 V~	> 60 dB
Normal Mode Interference Voltage	Noise quantity max. 1000 V ~	V dc	50dB
	Value of the measuring range at a time Max. 1000V~, 50Hz, 60Hz sinusoidal		
	Noise quantity max. 1000 V-	V~	>110dB

Response time (After manual range selection):

Measured Quantity/ Measured Response time	Response Time		Transient response for step function of the measured quantity
	Of Analog indication	Of digital indication	
VDC, VAC, A AC+DC, A AC	0.7 s	1.5 s	From 0 to 80 % of upper range limit.
30Ω...3 MΩ	1.5 s	2 s	
30 MΩ	4 s	5 s	From ∞ to 50 % of upper range limit.
	0.7s	1.5s	
nF, μF, °C,		Max. 1... 3 s	From 0 to 80 % of upper range limit.
300 Hz, 3KHz		Max 2 s	
30 KHz, 300 KHz		Max 0.7 s	
% (1 Hz)		Max 9 s	
% (≥10 Hz)		Max 2.5 s	



RISHABH
INSTRUMENTS
Measure, Control & Record with a Difference

RISHABH INSTRUMENTS PVT.LTD.

F-31, MIDC, Satpur, Nashik-422 007, India.

Tel.: +91 253 2202160, 2202202 Fax : +91 253 2351064

E-mail : India :- marketing@rishabh.co.in

International :- exp.marketing@rishabh.co.in

www.rishabh.co.in